

Adaptive integral backstepping controller for linear induction motors

Omar Mahmoudi, Abdelkrim Boucheta

Department of Electrical Engineering, University of Tahri Mohamed Bechar, Algeria

Article Info

Article history:

Received Jan 21, 2019

Revised Mar 1, 2019

Accepted Mar 10, 2019

Keywords:

Adaptive backstepping

Field oriented control

Integral action

Linear induction motor

ABSTRACT

Linear induction motors offer the possibility to perform a direct linear motion without the need of mechanical rotary to linear motion transformers. The main problem when controlling this kind of motors is the existence of undesirable behaviours such as end effect and parameter variations, which makes obtaining a precise plant model very complicated. This paper proposes an adaptive backstepping control technique with integral action based on Lyapunov stability approach, which can guarantee the convergence of position tracking error to zero despite of parameter uncertainties and external load disturbance. Parameter adaptation laws are designed to estimate mover mass, viscous friction coefficient and load disturbance, which are assumed to be unknown constant parameters; as a result the compensation of their negative effect on control design system. The performance of the proposed control design was tested through simulation. The numerical validation results have shown good performance compared to the conventional backstepping controller and proved the robustness of the proposed controller against parameter variations and load disturbance.

Copyright © 2019 Institute of Advanced Engineering and Science.

All rights reserved.

Corresponding Author:

Omar Mahmoudi,
Department of Electrical Engineering,
University of Tahri Mohamed Bechar,
B.P 417 Bechar 08000, Algeria.
Email: omaritomah@gmail.com

1. INTRODUCTION

Linear induction motors (LIMs) are widely used in industrial processes and transportation applications [1, 2]. The main advantage of the LIM is its ability to perform a direct linear motion without the need of any gear box or mechanical rotary to linear motion transformation [3].

The driving principle of the LIM is similar to that of a rotary induction motor (RIM), however, the control characteristics are more complicated and the parameters are time varying due to change of operating conditions, such as speed of mover, temperature and configuration of rail.[4, 5]

Field oriented control (FOC) is considered as the most popular high performance control method for induction machines. The main idea of the FOC is to decouple the dynamics of thrust force and rotor flux to make the control as simple as in a separately excited DC machine [6-8]. Unfortunately, a good performance of FOC can only be achieved by a precise plant model and it can be disturbed by parameter variations, which presents a big issue, because unlike RIM the model of LIM presents more complexity. Moreover, there are significant parameter variations in the reaction rail resistivity, the dynamics of the air gap, slip frequency, phase unbalance, saturation of the magnetizing inductance, and end-effects phenomenon [9-12], causing a difficulty in achieving a good control performance. Many researches have been done in modeling the LIM performance taken into consideration time varying parameters and end effect phenomenon [3, 8-10, 13]. However, there are always some modeling uncertainties due to undesirable behaviors.

The advancement in nonlinear control field gave a variety of solutions in dealing with parameter variations and load disturbance. One of these solutions is backstepping control, this last is a nonlinear control technique that has been widely applied in controlling LIMs [12, 14]. The basic idea of backstepping is the decomposition of a high order nonlinear control design problem into smaller steps, in which every step introduces a reference to stabilize the next one using the so called “virtual control” variables, until we reach the real control input that insures the global stability based on lyapunov function [12, 14, 15]. In addition, the adaptive version of backstepping control guarantees the global stability of the system despite of parameter uncertainties and variations thanks to parameter update laws [15].

In this paper we propose an adaptive backstepping control design based on field oriented control to achieve a desired position trajectory under the assumption of unknown mover mass, friction coefficient and load disturbance. The rest of the paper is organized as follows: in section 2, we introduce the basics of indirect field oriented control. Section 3 presents the proposed adaptive backstepping controller. In section 4, we show the simulation results followed by discussion. Finally, a conclusion is drawn in section 5.

2. INDIRECT FIELD ORIENTED CONTROL

Figure 1 shows the construction of a LIM. The primary is simply a cut-open and rolled-flat rotary motor primary, and the secondary usually consists of a sheet conductor using aluminum with an iron back for the return path of the magnetic flux. For a zero relative velocity, the LIM can be considered as having an infinite primary, in which case the end effects may be ignored [12].




Figure 1. Construction of a LIM

The fifth order model of the LIM in the d-q axis reference frame modified from a three phase Y-connected rotary induction motor model is given as [12, 16]:

$$\frac{di_{ds}}{dt} = -\frac{1}{\sigma L_s} \left(R_s + \left(\frac{L_m}{L_r} \right)^2 R_r \right) i_{ds} + \frac{\pi}{h} V_e i_{qs} + \frac{L_m R_r}{\sigma L_s L_r} \cdot \varphi_{dr} + \frac{P L_m \pi}{\sigma L_s L_r h} \cdot \varphi_{qr} \cdot v + \frac{1}{\sigma L_s} V_{ds} \quad (1)$$

$$\frac{di_{qs}}{dt} = -\frac{\pi}{h} V_e i_{ds} - \frac{1}{\sigma L_s} \left(R_s + \left(\frac{L_m}{L_r} \right)^2 R_r \right) i_{qs} - \frac{P L_m \pi}{\sigma L_s L_r h} \cdot \varphi_{dr} \cdot v + \frac{L_m R_r}{\sigma L_s L_r} \cdot \varphi_{qr} + \frac{1}{\sigma L_s} V_{ds} \quad (2)$$

$$\frac{d\varphi_{dr}}{dt} = \frac{L_m R_r}{L_r} i_{ds} - \frac{R_r}{L_r} \cdot \varphi_{dr} + \frac{\pi}{h} (V_e - P \cdot v) \varphi_{qr} \quad (3)$$

$$\frac{d\varphi_{qr}}{dt} = \frac{L_m R_r}{L_r} i_{qs} - \frac{\pi}{h} (V_e - P \cdot v) \varphi_{dr} - \frac{R_r}{L_r} \varphi_{qr} \quad (4)$$

$$F_e = K_f (\varphi_{dr} i_{qs} - \varphi_{qr} i_{ds}) = M \frac{dv}{dt} + f_c \cdot v + F_L \quad (5)$$

where R_s is stator resistance per phase, R_r is rotor resistance per phase, L_s is the stator inductance per phase, L_r is the rotor inductance per phase, L_m is the magnetizing inductance per phase, P is the number of pole pairs, h is the pole pitch, $\sigma = 1 - (L_m^2 / L_s L_r)$ is the leakage coefficient, V_e is the synchronous linear velocity, v is the mover linear velocity, i_{ds} and i_{qs} are the d-axis and q-axis stator currents, ϕ_{dr} and ϕ_{qr} are the d-axis and q-axis rotor fluxes, V_{ds} and V_{qs} are d-axis and q-axis stator voltages, $K_f = 3P\pi L_m / (2L_r h)$ is a force constant, F_e is the electromagnetic force, F_L is the external load disturbance, M is the total mass of the moving part and f_c is the viscous friction and iron-loss coefficient.

The main idea of the field oriented control is to render the behaviour of the LIM similar to that of a separately excited DC machine, this last gives the ability to control the electromagnetic force and rotor flux independently [7], [17]. The decoupling is realized by forcing the secondary flux linkage to align with the d-axis. As a result we get,

$$\phi_{qr} = 0, \quad \frac{d\phi_{qr}}{dt} = 0 \quad (6)$$

Using (6) and replacing in the rotor flux equations (3) and (4) we get,

$$\phi_{dr} = \frac{L_m}{1 + \tau_r s} i_{ds} \quad (7)$$

where s is the Laplace operator, and $\tau_r = L_r / R_r$ is the secondary time constant.

Replacing (6) in electromagnetic force equation (5) gives,

$$F_e = K_f \phi_{dr} i_{qs} \quad (8)$$

Viewing equations (7) and (8) we can see that the rotor flux and the electromagnetic force can now be controlled separately using stator currents i_{ds} and i_{qs} .

Using (6) and (4) the slip velocity can be written as

$$V_{sl} = V_e - Pv = \frac{hL_m}{\pi L_r \tau_r \phi_{dr}} i_{qs} \quad (9)$$

3. ADAPTIVE BACKSTEPPING CONTROL WITH INTEGRAL ACTION

The basic idea of the backstepping design is the decomposition of a complex nonlinear system into multiple single input-output first order subsystems, using the so-called “virtual control” variables [18], in which every control variable is forced to stabilize the previous subsystem generating a corresponding error which can be stabilized by convenient input selection via lyapunov stability [14, 16, 18, 19], The steps to design such controller for LIM position tracking are as follows:

Define the position tracking error

$$e_1 = d_{ref} - d \quad (10)$$

Its dynamic can be written as

$$\dot{e}_1 = \dot{d}_{ref} - \dot{d} = \dot{d}_{ref} - v \quad (11)$$

Consider the lyapunov function candidate

$$V_1 = \frac{1}{2} e_1^2 \quad (12)$$

Deriving V_1 and using the error dynamic equation (11) we obtain

$$\dot{V}_1 = e_1 \dot{e}_1 = e_1 (\dot{d}_{ref} - v) \quad (13)$$

Choosing the velocity stabilising function as

$$v_{ref} = k_1 e_1 + \dot{d}_{ref} \quad (14)$$

where k_1 is a positive design constant to be determined later, gives

$$\dot{V}_1 = -k_1 e_1^2 \leq 0 \quad (15)$$

which guarantees the stabilisation of our closed-loop control.

However the velocity v is not a real input, it's a "virtual control" input [19, 20], so we define the following velocity tracking error:

$$e_2 = v_{ref} - v \quad (16)$$

To ensure the convergence of the position tracking error to zero at the steady state despite the presence of disturbance and modeling inaccuracy of the system we introduce an integral action to the desired velocity as follows [15]

$$v_{ref} = k_1 e_1 + \dot{d}_{ref} + k_1' e_1' \quad (17)$$

where $e_1' = \int e_1(t) dt$ is the integral action of the position tracking error and k_1' is a positive design constant.

The dynamics of the velocity tracking error give,

$$\begin{aligned} \dot{e}_2 &= \dot{v}_{ref} - \dot{v} \\ &= \ddot{d}_{ref} + k_1 (\dot{d}_{ref} - v) + k_1' e_1 - \frac{F_e}{M} + \frac{f_c}{M} v + \frac{F_L}{M} \end{aligned} \quad (18)$$

Then the dynamics of e_1 can be rewritten as

$$\dot{e}_1 = -k_1 e_1 + k_1' e_1' + e_2 \quad (19)$$

Define another Lyapunov function

$$V_2 = \frac{1}{2} e_1^2 + \frac{1}{2} e_2^2 + \frac{k_1'}{2} e_1'^2 \quad (20)$$

Its time derivative is

$$\dot{V}_2 = e_1 \dot{e}_1 + e_2 \dot{e}_2 + k_1' e_1' \dot{e}_1 \quad (21)$$

Using (19), (20) and (21) we get,

$$\dot{V}_2 = -k_1 e_1^2 - k_2 e_2^2 + e_2 \left[e_1 (1 - k_1^2 + k_1') + k_1' k_1 e_1' + e_2 (k_1 + k_2) + \ddot{d}_{ref} - \frac{F_e}{M} + D.v + L \right] \quad (22)$$

where k_2 is a positive design parameter, $D = f_c / M$ is the normalized friction coefficient and $L = F_L / M$ is the normalized Load disturbance.

Now we can choose our force control input F_{e_ref} to cancel the undesirable behaviours and guarantee achieving the desired position trajectory.

If we choose

$$F_{e_ref} = M[e_1(1 - k_1^2 + k_1') + k_1'k_1e_1' + e_2(k_1 + k_2) + \ddot{d}_{ref} + D.v + L] \quad (23)$$

we get

$$\dot{V}_2 = -k_1e_1^2 - k_2e_2^2 \leq 0 \quad (24)$$

which guarantees the stabilization of our control in the closed-loop.

However, the real values of parameters M , D and L are unknown and can't be used, so we use their estimates \hat{M} , \hat{D} and \hat{L} instead:

$$\hat{F}_{e_ref} = \hat{M}[e_1(1 - k_1^2 + k_1') + k_1'k_1e_1' + e_2(k_1 + k_2) + \ddot{d}_{ref} + \hat{D}.v + \hat{L}] \quad (25)$$

The next step is to extract the update laws of estimated parameters, for that purpose we define the following parameter estimation errors:

$$\tilde{M} = M - \hat{M} \quad (26)$$

$$\tilde{D} = D - \hat{D} \quad (27)$$

$$\tilde{L} = L - \hat{L} \quad (28)$$

Using these definitions and substituting the force control in (25) to the velocity tracking error in (18) the dynamics of e_2 become,

$$\dot{e}_2 = \ddot{d}_{ref} + k_1(-k_1e_1 - k_1'e_1' + e_2) + k_1'e_1 - \frac{M - \tilde{M}}{M}\beta + D.v + L \quad (29)$$

where $\beta = [e_1(1 - k_1^2 + k_1') + k_1'k_1e_1' + e_2(k_1 + k_2) + \ddot{d}_{ref} + \hat{D}.v + \hat{L}]$

After few calculations we get,

$$\dot{e}_2 = -e_1 - k_2e_2 + \hat{D}.v + \hat{L} + \frac{\hat{M}}{M}\beta \quad (30)$$

Finally, we construct the final lyapunov function that includes all the system's error signals in order to derive the estimates update laws,

$$V_3 = \frac{1}{2}e_1^2 + \frac{1}{2}e_2^2 + \frac{k_1'}{2}e_1'^2 + \frac{1}{2\delta_1 M}\tilde{M}^2 + \frac{1}{2\delta_2}\tilde{D}^2 + \frac{1}{2\delta_3}\tilde{L}^2 \quad (31)$$

where δ_1 , δ_2 and δ_3 are positive design constants.

Assuming that M , D and L are constant parameters, we can write,

$$\dot{\tilde{M}} = -\dot{\hat{M}} \quad (32)$$

$$\dot{\tilde{D}} = -\dot{\hat{D}} \quad (33)$$

$$\dot{\tilde{L}} = -\dot{\hat{L}} \quad (34)$$

Using (32), (33), (34) and the error dynamics in (19) and (30) we calculate the time derivative of (31)

$$\begin{aligned} \dot{V}_3 &= e_1 \dot{e}_1 + e_2 \dot{e}_2 + k_1' e_1' e_1 - \frac{1}{\delta_1 M} \tilde{M} \dot{M} - \frac{1}{\delta_2} \tilde{D} \dot{D} - \frac{1}{\delta_3} \tilde{L} \dot{L} \\ &= -k_1 e_1^2 - k_2 e_2^2 + k_1' e_1' e_1 + e_2 \left(-e_1 + \frac{\tilde{M}}{M} \beta + \hat{D} v + \hat{L} \right) - \frac{1}{\delta_1 M} \tilde{M} \dot{M} - \frac{1}{\delta_2} \tilde{D} \dot{D} - \frac{1}{\delta_3} \tilde{L} \dot{L} + e_1 (-k_1' e_1' + e_2) \end{aligned} \quad (35)$$

We finally get

$$\dot{V}_3 = -k_1 e_1^2 - k_2 e_2^2 + \frac{\tilde{M}}{M} \left(e_2 \beta - \frac{1}{\delta_1} \dot{M} \right) + \tilde{D} \left(e_2 v - \frac{1}{\delta_2} \dot{D} \right) + \tilde{L} \left(e_2 - \frac{1}{\delta_3} \dot{L} \right) \quad (36)$$

In order to render the global lyapunov function negative we choose the update laws of the parameter estimates as:

$$\dot{\hat{M}} = \delta_1 e_2 \beta \quad (37)$$

$$\dot{\hat{D}} = \delta_2 e_2 v \quad (38)$$

$$\dot{\hat{L}} = \delta_3 e_2 \quad (39)$$

The resulting lyapunov function dynamics give

$$\dot{V}_3 = -k_1 e_1^2 - k_2 e_2^2 \leq 0$$

which guarantees the stability of the global system and the achievement of the desired position trajectory despite of load disturbance and undesirable behaviours.

The previous controller designing steps are summed up in the diagram in Figure 2:




Figure 2. Adaptive backstepping controller scheme

4. SIMULATION AND DISCUSSION

To investigate the performance of the proposed adaptive backstepping controller with integral action for the LIM position tracking, we run numerical simulation in which the effectiveness of the proposed controller under different operating conditions is tested (external load disturbance, friction and mover mass variation).

The obtained results are compared to those of conventional backstepping control technique. The LIM parameters used for simulation are shown in Table. 1.

Table 1. LIM parameters

Parameter	Value
R_s	3.4 (Ω)
R_r	1.95 (Ω)
L_s	0.1078 (H)
L_r	0.1078 (H)
L_m	0.1042 (H)
P	2
M	5.47 (Kg)
F_c	26.36 (Nm.s/rd)

4.1. Case 1 (known parameters)

First, we present the simulated results for a periodic step reference with known parameters and no load disturbance. The controller design parameters and update laws are chosen as follows: $k_1 = 10$, $k_1' = 0.1$, $k_2 = 80$, $\delta_1 = 0.001$, $\delta_2 = 0.8$, $\delta_3 = 500$. The position tracking response is shown in Figure 3a. The applied electromagnetic force is shown in Figure 3b. The stator current I_{qs} is shown in Figure 3c. And Figure 3d. shows the rotor fluxes.

The obtained results show good performance for both conventional and adaptive backstepping controllers when the parameters are known and invariant. The position tracking error converges to zero with fast response time about 0.5s, the decoupling between electromagnetic force and rotor flux is realized, and we can see that the rotor flux is kept constant in the steady state (Figure 3d) while the electromagnetic force is being controlled by the variation of quadratic stator current I_{qs} (Figure 3b. Figure 3c.).

Next, we test the robustness of the proposed control scheme under the existence of parameter uncertainties. For that purpose we devide the next simulation into three steps, each step presents a possible parameter variation as Case 2, 3, 4.




Figure 3. Adaptive backstepping position control of LIM with known parameters, (a) position tracking response, (b) electromagnetic force, (c) stator current I_{qs} , (d) rotor fluxes

4.2. Case 2 (load disturbance)

Case 2: a constant force disturbance of 10N is injected at $t=5s$ and removed at $t=7s$. The obtained results are presented in Figure 4.





Figure 4. Adaptive backstepping position control of LIM with applied load force of 10N, (a) position tracking response, (b) zoom in position, (c) electromagnetic force, (d) zoom in electromagnetic force, (e) stator current I_{qs} , (f) rotor fluxes.

4.3. Case 3 (1.5×D)

Case 3: friction coefficient variation equals to 1.5×D. The obtained results are presented in Figure 5.







Figure 5. Adaptive backstepping position control of LIM with $1.5 \times D$, (a) position tracking response, (b) zoom in position, (c) electromagnetic force, (d) stator current I_{qs} , (e) rotor fluxes.

4.4. Case 4 ($2 \times M$)

Case 4: mover mass variation equals to $2 \times M$. The results are presented in Figure 6.






Figure 6. Adaptive backstepping position control of LIM with $2 \times M$, (a) position tracking response, (b) zoom in position, (c) electromagnetic force, (d) stator current I_{qs} , (e) rotor fluxes.

The simulated results prove that adaptive backstepping controller is insensitive against load disturbance and can reject it with nearly no overshoot, in contrary of conventional backstepping where the control is sensitive causing a failure in position tracking with a non-null static error (Figure 4a. Figure 4b.). The electromagnetic force generated by the adaptive controller has risen by 10N after applying the load force in order to cancel the disturbance (Figure 4c. Figure 4d.).

In case 3, where the friction coefficient has risen by 50%, we can see that the response time for conventional backstepping has risen slightly to 0.7s, while for the adaptive controller it hasn't been affected (Figure 5a. Figure 5b.), that shows that the proposed technique is insensitive against friction force variation too.

In the case of mover mass change to double value, we can observe that the adaptive backstepping controller is always insensitive and can achieve the desired position trajectory with fast response time and no overshoot, while the conventional backstepping controller response has overshoot before it could achieve the desired trajectory causing a delay in response time as well (Figure 6a. Figure 6b.).

The previous numerical validations show good performance and prove the robustness of the adaptive backstepping controller against sudden changes thanks to parameter update laws based on Lyapunov stability, which guarantees the stability of the global system despite of load disturbance and parameter variations. The estimated parameters are shown in Figure 7. We can observe from the figure that the estimated parameters converge to the real values with acceptable response time and error range allowing the controller to track the desired trajectory despite of parameter changes.




Figure 7. Estimated parameters, (a) load force disturbance, (b) viscous friction coefficient, (c) mover mass

5. CONCLUSION

This paper has demonstrated the application of an adaptive backstepping controller with integral action to track a position reference for LIM. First, the indirect field oriented control was used to decouple the control of electromagnetic force and rotor flux. Then, an adaptive backstepping controller was designed and parameter update laws were extracted, to achieve a desired position reference under the assumption of parameter uncertainties, and the existence of external load force disturbance. The effectiveness of the proposed controller was tested through numerical simulation under different operating conditions. The obtained results show good tracking performance compared to the conventional backstepping controller, and prove the ability of the adaptive backstepping design to reject external load disturbance without overshoot, and its insensitivity against sudden parameter variations thanks to parameter update laws. Finally, the robustness of the adaptive backstepping controller was successfully confirmed.

REFERENCES

- [1] P. K. Huang, "Recurrent fuzzy neural network controlled linear induction motor drive based on genetic algorithm," M.S Thesis, Chung Yuan Christian University, 2002.
- [2] C. Y. Hung, "Adaptive control for rotary induction motor and linear induction motors," M.S Thesis, Chung Yuan Christian University, 2001.
- [3] N. H. Quang, N. P. Quang, N. N. Hien, N. T. Binh., "Min Max Model Predictive Control for Polysolenoid Linear Motor," *International Journal of Power Electronics and Drive System (IJPEDS)*, Vol. 9, No. 4, pp. 1666-1675, December 2018.
- [4] S. P. Bhamidi, "Design of a single sided linear induction motor (slim) using a user interactive computer program," M.S Thesis, Missouri-Colombia University, 2005.
- [5] R. J. Kaye and E. Masada, "Comparison of Linear Synchronous and Induction Motors," *Urban Maglev Technology Development Program Colorado Maglev Project*, Internal report, June 2004.
- [6] T. Hualin and C. Jie, "Field orientation and adaptive backstepping for induction motor control," *Proc of IEEE Industry Applications Conf*, pp. 2357-2363, 1999.
- [7] R. J. Wai and C. C. Chu, "Indirect Field-oriented Linear Induction Motor Drive with Petri Fuzzy-neural-network Control," *Proc of International Joint Conf on Neural Networks*. Montreal, Canada, July 31-August 4, 2005
- [8] S. Motlagh and S. S. Fazel, "Indirect vector control of linear induction motor considering end effect," *3rd Power Electronics and Drive Systems Technology Conf*, 2012 (PEDSTC), pp. 193 – 198, February 2012.
- [9] R. J. Wai. and W. K. Liu, "Nonlinear decoupled control for linear induction motor servo-drive using the sliding-mode technique," *IEE Proc of Control Theory and Applications*, Vol. 148 No. 3, pp. 217-231, 2001.
- [10] A. Accetta, M. Cirrincione, M. Pucci, and G. Vitale, "Neural sensorless control of linear induction motors by a full-order luenberger observer considering the end effects," *IEEE Trans on Industry Applications*, Vol. 50 No. 3, pp. 1891-1904, 2014.
- [11] F. Alonge, M. Cirrincione, F. D'Ippolito, M. Pucci, and A. Sferlazza, "Parameter identification of linear induction motor model in extended range of operation by means of input-output data," *IEEE Trans on Industry Applications*, Vol. 50 No. 2, pp. 959-972, 2014.
- [12] A Boucheta, I. K. Bousserhane, A. Hazzab, B. Mazari, and M. K. Fellah, "Adaptive backstepping controller for linear induction motor position control," *Int. Journal for Computation and Mathematics in Electrical and Electronic Engineering*, Vol. 29 No. 3, pp. 789-810, 2010.
- [13] J. Duncan, "Linear induction motor-equivalent-circuit model," *IEE Proc. Electr. Power Appl*, Vol. 130 No. 1, pp. 51-57, 1983.
- [14] F. J. Lin, and C. C. Lee, "Adaptive backstepping control for linear induction motor drive to track periodic references," *IEE Proc. Electr. Power Appl*, Vol. 147, 2000.
- [15] Y. Tan, J. Hu, J. Chang and H. Tan. "Adaptive Integral Backstepping Motion Control and Experiment Implementation," *IEEE Int. Conf on Industrial Technology*, 2000:1081-1088.
- [16] R. J. Wai, F. J. Lin and S. P. Hsu, "Intelligent backstepping control for linear induction motor drives," *IEE Proc. Electr. Power Appl*, Vol. 148, No. 3, May 2001.
- [17] M. Es-Saadi, M. Khafallah, H. Chaikhy, "Using the Five-Level NPC Inverter to Improve the FOC Control of the Asynchronous Machine," *International Journal of Power Electronics and Drive System (IJPEDS)*, Vol. 9, No. 4, pp. 1666-1675, December 2018.
- [18] H. Tan, J. Chang, "Field orientation and adaptive backstepping for induction motor control," *Proc. IEEE-IAS Annu. Meeting*, pp. 2357-2363, 1999.
- [19] I. Kanellakopoulos, P. V. Kokotovic, and A. S. Morse, "Systematic design of adaptive controller feedback linearizable systems," *IEEE trans. Auto. Control*, Vol. 36 No. 11, pp. 1241-53, 1991.
- [20] M. Krstic, I. Kanellakopoulos, P. V. Kokotovic, *Nonlinear and Adaptive Control Design*, Wiley, New York, 1995.